
#### **SPECIFICATIONS**

Model			KDS-	6000	BB									
Output power (RMS)			1.5 kW											
Transducer			DHU-6302-80 kHz DHU-6302-BB											
Output free	uency	/	80 to 90 kHz (0.1 kHz step) 130 to 210 kHz (0.1 kHz step)											
Tilt angle			5° to -90° (1°step)											
Beam angle	2		8° to 12°											
TD stroke			150	to 380	0 mm	(Reco	omme	ended	value	e 150	mm)			
Display size	e and :	type			or wit							)		
Basic ranges			10 to 1000 (m), 30 to 3000 (ft), 10 to 600 (fm),10 to 700 (l.fm) (8 ranges can be set to users choice)											
Range units	5		m, ft	, fm, l	l.fm									
Scanning sector Sonar mode angles														
	tom scan mode													
360° Scanning		Scanning range (m)	20	40	60		100	120	160	180	200	240		
(extracts)		ing time (sec.) 5° step	6.3	8	10	11.8	14						43.3	
		ing time (sec.)10° step	3.7	4.7	5.6	6.5	7.6		10.6	11.5	12.5	14.4	22.4	
		ing time (sec.)15° step	3.3	3.7	4.3	4.9	5.7	6.4	7.9	8.2	8.9	10.3	15.7	
	Scanni	ing time (sec.)20° step	3.3		3.8	4.2	4.8	5.2	6.4	6.6	7.3	8.1	12.2	
Bearing cer			1 °st											
Presentation modes			Sonar, Off-center, Bottom scan, Echo sounder,											
			2 Mode Display, One line											
Off-Center					k, Left									
Target lock			Reverse, Horizontal, Horizontal + Vertical, Marker + Horizontal, Marker + Vertical											
Presentation colors			8 colors, 16 colors											
Functions			TVG , Color rejection, Dynamic range, Compass display, Pulse width, Output power control, Noise reduction, A-scope, CM key, Frequency bandwidth, Image correction, Bearing display, TD auto up, Sona-Tone™											
Language			English, Japanese, Korean, Spanish, Thai, Traditional Chines, Greek, Italian, Portuguese, Burmese											
Input data format and sentences			NMEA0183 GGA, GLL, HDG, HDM, HDT, RMC, THS, VTG, ZDA											
Output data format and sentences			NMEA0183 DBT, DPT, GGA, GLL, MTW, RMC, TLL, VTG, ZDA											
NMEA port	s				nput /			,	,	,				
Power supp	oly	Processor unit	10.8 to 31.2 VDC											
	· -	Hull unit	10.8 to 31.2 VDC											
Power consur	nption		70 W or less (24 VDC)											
			70 W or less (24 VDC) -15 °C to + 55 °C											
			4 5 6	C to	EE C			-	-					
Operating t Water prote		rature	-15 °	C 10 ·	+ 55 `	C								

#### **CONNECTIONS**



#### **EOUIPMENT LIST**

Standa


Ontio

Safetv

For details, please contact:

lard equipment	Processor unit			
	Operation unit	1		
	Hull unit	1		
	Accessories for Processor unit	1		
	Installation materials for Hull unit	1		
	TD position alarm	1		
	DC power cable	1		
	Operation manual, Installation manual, Quick Reference	1		
ons	Remote controller, PCV TD tank, FRP TD tank, Shaft guide for FRP tank AC rectifier unit, Connecting cable, 17 inch LCD monitor			

#### **DIMENSIONS AND WEIGHT**



• Design and specifications are subject to change without notice

To ensure proper and safe use of the equipment, please carefully

precaution read and follow the instructions in the Operation Manual



wa Office: 2-13-24 Tamagawa, Ota-ku, Tokyo, 146-0095 Japan Tel: +81-3-3756-6501 Fax: +81-3-3756-6509 Uenohara Office: 5278 Uenohara, Uenohara-shi, Yamanashi, 409-0112 Japan Tel: +81-554-20-5860 Fax: +81-554-20-5875

overseas@koden-electronics.co.jp

www.koden-electronics.co.jp



### **Features**

- Change frequency on the go with our advanced Broadband Technology
- ► Massive improvement in scan speed, making detection of fish schools much faster
- Clearest possible images with our digital signal processing
- All setup and user settings changed instantly by utilizing **Conditional Memory function**



▶ Black Box sonar with 17 inch LCD Monitor available (Option)

# **Digital Sonar**

# Advanced Broadband Technology


KDS-6000BB is world first Broadband searchlight sonar. The 80 to 90 kHz frequency or 130 to 210 kHz frequency can be selected depending on the Transducer. The most suitable output frequency can be selected in 0.1 kHz step depending on the fishing method and the target species from closer range to longer range. Selection of frequency is as easy and quick as tuning a radio. Flexible selection of frequency enables the user to stay away from interference with the sounders on the other vessels.

# Clearest possible images with our digital signal processing

Both of high resolution in closer range and noise reduction performance in longer range are materialized at high level with newly-developed digital signal processing, KDP V.


### Massive improvement in scan speed

Scanning speed is remarkably increased by adding 15° and 20° in scanning sector angle steps. It can detect surrounding fish schools guickly.




Comparison of scanning area of the same time period


### • Six different presentation modes




Sonar mode Search around the ship




Bottom scan mode Reflected echo from underwater and sea bottom




Off-center mode Show more information of ahead



Echo sounder mode Image like Echo sounder



Sonar x 2 mode Two different frequencies




One line display mode Show vertical Sonar image like an echo sounder image in the Sub-screen

# • CM keys





Black box type



Newly-desighed compact Hull unit allows for saving the space on your vessel.

# 80 kHz screen images





Sardine at 80.0 kHz

Red bream at 80.0 kHz

# **KDS-6000BB**

Six of CM (Condition Memory) keys offer the user to preset all the current settings and recall them instantly. It is like six sonars in one unit.


KDS-6000BB comes in black box. The user can select a monitor from the market or the optional 17 inch LCD monitor

# • Space-saving Hull unit



Hull unit **DHU-6301** 

**Transducer unit DHU-6302** 



Depth of 680m at 80.0 kHz